


# QUANUM ELITE

## TX CAMERA COMBO MICRO CAM VTX

25mW 5.8GHz



### Features

1. Super small and lightweight
2. Easy install, plug and play
3. Button control instead of switch to change channels

### Operating instructions

How to change frequencies (bands/channels)

Press Band/Channel button once to change channel.

Push and hold button for 2 seconds to change band.

## Specifications

Transmitter power: 25mW

Input power: 2.5–5V

Camera resolution: 600TVL

Min illumination: 1 lux

Field of view: 120° viewing angle

Antenna dimensions: 20mm X 25mm diameter

Antenna: 3 lobe right hand circular polarized

Video output: NTSC

Frequency: 5.8GHz 5 bands 40 channels, with

Raceband: 5658-5917

Bands: see below channel table.

Push button operation, long press for band, short press for channel

2 row LED indicators, 5 LED for band, 8 LED for channel

PCB color: blue

Size: 20x17mm(LxW)

Weight: 4.5g

Band \ CH	CH							
	CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8
Band 1(F)	5740	5760	5780	5800	5820	5840	5860	5880
Band 2(E)	5705	5685	5665	5645	5885	5905	5925	5945
Band 3(A)	5865	5845	5825	5805	5785	5765	5745	5725
Band 4(R)	5658	5695	5732	5769	5806	5843	5880	5917
Band 5(B)	5733	5752	5771	5790	5809	5828	5847	5866